

IMAGE PROCESSING APPARATUS

FIELD OF THE INVENTION

The invention relates to an image processing apparatus.

DESCRIPTION OF THE PRIOR ART

In facsimile and other reproduction processes, the intention is to output an image which has as near as possible the same colours as the input image. In practice, 10 this can be difficult because the colour gamut of the input image and input device does not always coincide with the output gamut available from the output device and output medium. The ICC provides four fixed rendering intents, Absolute, Relative, Perceptual and Saturation.

15 Absolute will try and reproduce a colormetrical
rendition, any input image information outside the gamut of
the output media will be lost.

Relative will map the input media white point to the output media white point but again will lose any image data outside the output media black point and output gamut. In addition the white point mapping can introduce a colour cast in the output image from the original.

25 Perceptual will perform white and black point mapping
in addition to fitting the two media gamuts. This may
introduce some colour cast in the output image from the
original but since the whole range is mapped loss of image
detail should not occur. However it does map the image
range to the output media range and as such changes the
look of the image, so in general will not produce an exact
30 facsimile of originals which are inside the output gamut.

Saturation is not considered here as it is not normally used in the graphics arts industry.

35 Each method of rendering described above will provide a different result and it is time consuming for an operator to decide which is the best approach.

SUMMARY OF INVENTION

In accordance with the present invention, image processing apparatus comprises an input device; an output device; and a processor coupled to the input and output devices, the processor being adapted to compare the tone range of an image input via the input device and the tone range provided by the output device, and

We have devised apparatus which can automatically determine the most appropriate rendering method and which achieves satisfactory results in most cases without 20 clipping out of range tones.

In step (i), the white and black points will typically not be remapped although in some cases they could be adjusted. Similarly in step (ii), it may be that not all points outside the gamut will be mapped inside.

25 In some cases, mapping the tone ranges alone may not
yield an entirely satisfactory result. Preferably,
therefore, step (ii) further comprises determining if the
input colour gamut of the input device and image falls
outside the output colour gamut of the output device and
output medium by more than a predetermined amount and, if
30 it does, mapping the input colour gamut to the output
colour gamut using a perceptual mapping algorithm.

35 The predetermined amount could be zero but typically is around 12%. Thus, in cases where the input image includes unusual proportions of extreme colours, this can be overcome by using a perceptual mapping algorithm.

For convenience, the processor will operate on the tone ranges in Profile Connection Space since modern input and output devices are provided with respective profiles for converting image data into PCS. However, it will be 5 readily apparent that the invention is equally applicable to operate on tone ranges in other colour spaces.

In order to minimise the degree of mapping which takes place, preferably in step (ii), if only one extreme of the 10 input tone range falls outside the output tone range, the method comprises maintaining the other extreme substantially constant and mapping the remainder of the input tone range proportionally.

Typically, the extremes of the input tone range will be compared with 2-98% of the output tone range. This is 15 because the extremities may have multiple solutions in typical ICC profiles, i.e. there is not a unique L' value that corresponds to 0% or 100%. However, using values just in from the minimum and maximum values tend to give better defined L' results. 2% and 98% are typical values, 20 although this does not exclude other points or methods being used to find the L' range of the output media.

BRIEF DESCRIPTION OF THE DRAWINGS

An example of apparatus according to the invention will now be described with reference to the accompanying 25 drawings, in which:-

Figure 1 is a block diagram of the apparatus;

Figure 2 is a flow diagram illustrating operation of the processor shown in Figure 1; and,

Figure 3 illustrates graphically the processes 30 outlined in Figure 2.

DETAILED DESCRIPTION OF EMBODIMENT

The apparatus shown in Figure 1 comprises an input device 1 such as an input scanner associated with an ICC profile 2. This profile will typically define the mapping 35 of input image information into PCS. Output data from the input device 1 is fed to a processor 3 which then maps the data in the manner to be described below using output

profile data 4 to an output device 5 such as an output scanner.

The processor 3 operates on data in FCS in which the colour of each pixel of the image is defined by components 5 L^*ab in a conventional manner. Tone is defined by the component L^* . Input data from the input device 1 is first reviewed by the processor 3 to determine the white and black points (Image ewL^* and Image ebL^*). These extremes of the input tones are compared with extremes 10,11 (Figure 10 3) of the output tones available. If both the image white and black points fall within the range defined by the extremes 10,11 as shown at 12 then each input tone can be exactly matched to a corresponding output tone and an absolute rendering is produced. This is indicated by a row 15 20 in Figure 2.

If the image white point falls outside the white extreme point 10 of the output profile as shown at 13 in Figure 3 then the image data is simply mapped to bring the white point into gamut while the black point is 20 substantially unchanged. This gives a gradual change where most of the image remains untouched and only the points out of gamut are moved. This is indicated at row 21 in Figure 2.

In practice, the extreme points of the output profile 25 are set just inside the actual extreme points representing 2% and 98% output L^* respectively. The reason for this is that points just inside the output media range of 0% to 100% may be more clearly defined when examining a typical ICC profile.

30 Similarly, if the image black point lies outside the output profile black extreme 11 as shown at 14 then the black point is mapped to the output black point while the white point remains substantially unchanged.

For these mapping operations, any conventional tone 35 mapping technique can be used.

If both the white and black image points lie outside the output range as shown at 15 then both points are mapped

into the range using the simple mapping method. This is shown at row 22 in Figure 2. In this case, however, it is more likely that a significant proportion of the input colour gamut will lie outside the output colour gamut in 5 which case instead of performing a simple mapping, the input range and colour gamut are mapped onto the output range and colour gamut to produce a visually pleasing result. This is indicated by row 23 in Figure 2.

10 Although the gamut mapping using the perceptual technique has been described for use when both black and white points have to be mapped, it could also be used in the other modes mentioned above.

15 Typically, perceptual mapping will be used if more than 12% of the colour input gamut falls outside the output gamut. In practice, it is undesirable to use perceptual mapping as soon as any part of the input image is outside the output gamut. Some "clipping" is generally acceptable and it was found that 12% was about the point where full 20 gamut mapping gave a better result than simply range mapping.

A simple code flow of the process is presented below:

1) Find Image ew / eb points in Lab

These will be the Absolute targets i.e. the desired reproduction

25 Image EW

Image EB

2) Find the achievable targets on the output (2% and 98%) expressed in L*

30 Look for this value by looking for all output values to be in the range 2% to 98% just inside gamut. Find the L*'s inside gamut to achieve this. This can be done by using the colour of the original image white and black points and ensuring that all output channels are within range, or testing some neutralised form of the input 35 values.

Output White

Output Black

